



COLOR CODE			
BK	BLACK	P	PINK
BL	BLUE	PR	PURPLE
BR	BROWN	R	RED
C	COPPER	T	TAN
G	GREEN	V	VIOLET
GY	GRAY	W	WHITE
O	ORANGE	Y	YELLOW
G/Y	GREEN WITH YELLOW STRIPE		

* THESE COMPONENTS MAY NOT APPEAR ON ALL MODELS.
WIRING IS SCHEMATIC

10	14	150	3321
9	16	200	3122
8	10	150	3321
7	12	150	3321
6	16	150	3321
5	18	150	3321
4	14	125	3173
3	16	125	3173
2	18	125	3173
1	18	105	1015
WIRE NO	GAGE	TEMP C°	UL STYLE

INSTALLATION OF RANGE

CONNECT ONLY TO 3-WIRE SINGLE PHASE A.C. SERVICE OF THE VOLTAGE INDICATED ON THE RANGE SERIAL PLATE. CONNECTIONS SHOULD BE MADE IN ACCORDANCE WITH LOCAL REQUIREMENTS AND SUPPLY WIRING BROUGHT INTO THE RANGE THROUGH THE OPENING IN THE ENTRANCE PLATE INTENDED FOR 3/4" OR 1" CONDUIT. IF A SERVICE CORD IS USED, STRAIN RELIEF SHOULD BE PROVIDED. THE SUPPLY CIRCUIT NEUTRAL MUST BE CONNECTED TO THE MIDDLE TERMINAL OF THE RANGE TERMINAL BLOCK.

WARNING - ELECTRICAL GROUNDING INSTRUCTIONS

THIS APPLIANCE MUST BE PERMANENTLY GROUNDED IN ACCORDANCE WITH THE NATIONAL ELECTRICAL CODE AND LOCAL CODES AND ORDINANCES. FRAME OF THIS APPLIANCE IS CONNECTED TO NEUTRAL BY A GROUND STRAP OR WIRE. IF USED IN MOBILE HOME OR IF LOCAL CODES DO NOT PERMIT FRAME GROUNDED TO NEUTRAL, REMOVE GROUND STRAP OR WIRE FROM APPLIANCE AND CONNECT SEPARATE GROUND WIRE BETWEEN APPROVED GROUND AND FRAME OF APPLIANCE. CONNECT NEUTRAL TERMINAL OR LEAD TO BRANCH CIRCUIT NEUTRAL IN USUAL MANNER.